

Analogue Wall Sounder Beacon

CHQ-WSB2



Features

- ▶ Single Loop Address - addressed via the TCH-B100 Hand Held Programmer
- ▶ Variable Sound Output
90 ~ 102 dB(A) (± 2 dB(A)) output at 1 metre
- ▶ Sounder and Beacon can operated independently*¹
- ▶ 0.5 or 1Hz flash frequency*¹
- ▶ High Intensity LED technology
- ▶ Fits Hochiki Standard or Isolator Base
- ▶ 51 User-Selectable Tones (all tones EN54-3 approved)
- ▶ Auto-Shutdown feature prevents noise pollution*¹
- ▶ 'O' Rated Beacon to EN54-23
- ▶ Available with Red or White LEDs
- ▶ Available with Red or White case
- ▶ Weatherproof Kit available

Description

Model CHQ-WSB2 is an addressable loop powered Wall Sounder Beacon innovatively designed to provide a range of tones and volumes with a maximum output of up to 102dB(A) (± 2 dB(A)) with low current consumption. The unit features an integral beacon within the horn utilising high intensity LED technology and is designed to fit to the Standard Base (YBO-R/3(RED) & YBO-R/SCI(WHT)) or the Isolator Base (YBO-R/SCI(RED) & YBO-R/SCI(WHT)). The sounder is IP rated to IP21 for internal use but it can be made weatherproof by utilising the WS2-WPK Weatherproof Kit, which consists of a specialised back box and gasket set.

Also incorporates an auto shutdown mode*¹ which allows the user to set a fixed time within which the sounder will operate, before automatically silencing itself, ideal for minimising noise pollution.

Specification

Ordering Codes	CHQ-WSB2/WL, CHQ-WSB2/RL, CHQ-WSB2(WHT)/WL, CHQ-WSB2(WHT)/RL (see page 2 for further details)
Operating Voltage	17 ~ 41 Vdc
Quiescent Current (typ)	150 μ A (with YBO-R/3(RED) & YBO-R/3(WHT)) 200 μ A (with YBO-R/SCI(RED) & YBO-R/SCI(WHT))
Sounding Current (typ)	2 mA (90 dB(A) (± 2 dB(A)) @ 1 m) ~ 8 mA (102 dB(A) (± 2 dB(A)) @ 1 m)
Additional Current when Beacon active	+ 7 mA
Sound Output (at 1 metre)	90 ~ 102 dB(A) (± 2 dB(A)) @ 24 Vdc or above
Number of Tones	51
Tone Frequency Range	300 Hz ~ 2850 Hz
Operating Temperature Range	-10 °C to +50 °C
Storage Temperature Range	-30 °C to +70 °C
Maximum Humidity	95% RH - Non Condensing (at 40 °C)
Colour/Case Material	Red or White / PC ABS
Lens Material	Translucent PC
Ingress Protection Rating	IP21 (IP65 with WS2-WPK)
Weight (g)/Dimensions (mm)	164 / H112 x W112 x D67
Base Fixing Centres (mm)	48 ~ 74

*¹ Panel compatibility dependant.

Note: Although the TCH-B100 Hand Held Programmer will allow addresses between 128 and 255 to be programmed into the CHQ-WSB2, addresses 1 to 127 ONLY should be used.

Hochiki Europe (UK) Ltd. reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki Europe (UK) Ltd. to be a complete and up-to-date description.

How to choose your Hochiki VAD

Our VAD ratings comprise three parts, **X-Y-Z**

where **X** denotes the category, either “O” for Open, “W” for Wall or “C” for ceiling

where **Y** denotes the maximum mounting height (m)

where **Z** is the width and length (m) of the coverage floor area

For example **C-3-5** means the VAD is in the Ceiling category, can be mounted at a maximum ceiling height of 3 metres and produces a 5 metre x 5 metre coverage.

What type of VAD?	Which case colour?	Which LED colour?	Product	EN54-23 Ratings*4			
				1	2	3	
Base Sounder Beacon	Ivory case	White LEDs	YBO-BSB2/WL	'O' Rated			
		Red LEDs	YBO-BSB2/RL				
	White case	White LEDs	YBO-BSB2(WHT)/WL				
		Red LEDs	YBO-BSB2(WHT)/RL				
Wall Sounder Beacon	Red case	White LEDs	CHQ-WSB2/WL				
		Red LEDs	CHQ-WSB2/RL				
	White case	White LEDs	CHQ-WSB2(WHT)/WL				
		Red LEDs	CHQ-WSB2(WHT)/RL				
Ceiling Beacon	Ivory case	Red LEDs	CHQ-CB/RL	O	C-3-7.5	C-3-10	
		White LEDs	CHQ-CB/WL	C-3-5	C-3-7.5	C-3-10	
			CHQ-CB/WL-15	O	C-3-10	C-3-15	
	White case	Red LEDs	CHQ-CB(WHT)/RL	O	C-3-7.5	C-3-10	
		White LEDs	CHQ-CB(WHT)/WL	C-3-5	C-3-7.5	C-3-10	
			CHQ-CB(WHT)/WL-15	O	C-3-10	C-3-15	
	Red case	Red LEDs	CHQ-CB(RED)/RL	O	C-3-7.5	C-3-10	
		White LEDs	CHQ-CB(RED)/WL	C-3-5	C-3-7.5	C-3-10	
			CHQ-CB(RED)/WL-15	O	C-3-10	C-3-15	
	Wall Beacon	Ivory case	White LEDs	CHQ-WB/WL	W-2.4-5	W-2.4-6	W-2.4-7
			Red LEDs	CHQ-WB/RL	O	O	W-2.4-5
		White case	White LEDs	CHQ-WB(WHT)/WL	W-2.4-5	W-2.4-6	W-2.4-7
Red LEDs			CHQ-WB(WHT)/RL	O	O	W-2.4-5	
Red case		White LEDs	CHQ-WB(RED)/WL	W-2.4-5	W-2.4-6	W-2.4-7	
		Red LEDs	CHQ-WB(RED)/RL	O	O	W-2.4-5	

*4 Ratings are all based on 0.5Hz frequency.

Current when Beacon active

CHQ-CB/WL&RL & CHQ-WB/WL & RL	mA	6	12	17
CHQ-CB/WL-15	mA	6	12	38
CHQ-WSB2/WL&RL	mA (Beacon Only)	7 (one setting only)		
YBO-BSB2/WL&RL	mA (Beacon Only)	7 (one setting only)		

For CHQ-CB/WL & RL Default setting is **C-3-7.5**

For CHQ-CB/WL-15 Default setting is **C-3-15**

Note: Our VAD product codes feature “WL” which means white LEDs and “RL” which means red LEDs.

For details of O Rating for Ceiling Beacon please see Application Note **AP131**.

For details of O Rating for Wall Sounder Beacon see Application Note **AP132**.

For details of O Ratings for Base Sounder Beacon please see Application Note **AP133**.